

IMPORTANT SAFETY INFORMATION. READ AND FOLLOW ALL SAFETY INSTRUCTIONS. Follow label information and instructions concerning Wet or Damp Locations, installation near combustible materials, insulation, building materials, and proper lamping. Do not install in areas subject to combustible vapors or gases. Before wiring to power supply and during servicing or relamping, turn off power at fuse or circuit breaker. **All servicing or relamping must be performed by qualified service personnel. Product must be grounded to avoid potential electric shock or other potential hazard. Product must be mounted in locations and at heights and in a manner consistent with its intended use, and in compliance with the National Electrical Code and local codes.** The use of accessory equipment not recommended by the manufacturer or installed contrary to instructions may cause an unsafe condition. Do not block light emanating from product in whole or part, as this may cause an unsafe condition. Do not allow items such as drapes, curtains, screens or the like to come into contact with the product or to block light from the product, as this may cause an unsafe condition.

INSTALLATION INSTRUCTIONS CFR9 EB Series

Housing Installation:

Install fixture housing into ceiling per Instruction Sheet supplied with housing.

Wiring:

Clamp the incoming ground wire to the J-Box with the green screw and cup washer.

Single circuit operation:

Connect the ground leads to the fixture ground in the junction box. Wire the two white leads to the incoming common. Wire the two black leads to the incoming line.

Two circuit operation:

Connect the ground leads to the fixture ground in the junction box. Wire the #1 white lead to the one incoming common. Wire #1 black lead to the incoming line in the same circuit. This circuit will operate the center lamp. Wire the remaining white lead to the second incoming common. Wire #1 black lead to the second incoming line circuit. This circuit will operate the outer lamps.

Trim Installation:

1. Remove both wing and hex nuts from socket holder assembly in fixture housing. This assembly will disengage from long mounting studs above.
2. Place trim ring over reflector.
3. Insert reflector with trim ring through hollow studs in socket holder assembly and secure finger tight with hex nuts.
4. Push socket holder with reflector through long studs in housing and secure with wing nuts.
5. Lamp fixture with three compact electronic fluorescent 18W lamps (Catalog No. CFR918EB, CFR918EBDM) or three compact electronic fluorescent 26W lamps (Catalog No. CFR926EB, CFR926EBDM).

